

QSK60-G4

Fuel Optimized



Description

The QSK60 is a V 16-cylinder engine with a 60-litre displacement. This Quantum series utilizes sophisticated electronics and premium engineering to provide outstanding performance levels, reliability, and versatility for Standby, Prime and Continuous Power applications.

Features

The QSK60 uses the Cummins High Pressure Injection (HPI) PT full authority electronic fuel system. Featuring a high pressure (HPI-PT) full authority fuel system, that has exceptional fuel efficiency. The CM2250 ECM provides the Power Generation Interface (PGI), the widely accepted SAE J1939 industry standard CAN based communication network and advanced engine protection, ensuring faster connectivity along with a superior fault-finding capability.

CTT (Cummins Turbo Technologies)
HX82/HX83 turbocharging utilizes exhaust energy with greater efficiency for improved emissions and fuel consumption.

Low Temperature After-cooling - Two-pump Two-loop (2P2L)

Ferrous Cast Ductile Iron (FCD) Pistons -High strength design delivers superior durability.

G-Drive Integrated Design - Each component has been specifically developed and rigorously tested for G-Drive products, ensuring high performance, durability, and reliability.

Service and Support - G-Drive products are backed by an uncompromising level of technical support and after sales service, delivered through a world class service network.

Coolpac Integrated Design - Products are supplied complete with cooling package and air cleaner kit for a complete power package. Each component has been specifically developed and rigorously tested for G-Drive products, ensuring high performance, durability, and reliability.



This engine has been designed in facilities certified to ISO9001 and manufactured in facilities certified to ISO9001 or ISO9002.

This equipment has been designed and tested to meet EU product safety regulations. Material compliance declaration is available upon request

1500 rpm (50 Hz ratings)

Gross engine output			Net engine output			Typical generator set output					
Standby	Prime	Prime Base Standby Prime Base Standby (ESP)		Prime (PRP)		Base (COP)					
kWm/BHP				kWm/BHP		kWe	kVA	kWe	kVA	kWe	kVA
1915/2567	1730/2319	1415/1897	1848/2478	1682/2255	1367/1833	1800	2250	1638	2047	1331	1664

1800 rpm (60 Hz ratings)

Gross engine output			Net engine output		Typical generator set output						
Standby	Prime	Base	Standby	Prime	Base	Standby (ESP)		Prime (PRP)		Base (COP)	
kWm/BHP		kWm/BHP		kWe	kVA	kWe	kVA	kWe	kVA		
-	-	-	-	-	-	-	-	-	-	-	-

General Engine Data

Fuel Rating	FR60194
Туре	4 cycle, turbocharged, After-cooled
Bore mm	159
Stroke mm	190
Displacement litre	60.2
Cylinder block	16 cylinder
Battery charging alternator	55 amps
Starting voltage	24-volt
Fuel system	Direct Injection Cummins HPI
Fuel filter	Spin-on fuel filters with water separator
Lube oil filter type(s)	Spin-on full flow filter
Lube oil capacity (I)	280
Flywheel dimensions	SAE 0

Coolpac Performance Data

Cooling system design	2 pump - 2 loop
Coolant ratio	50% ethylene glycol; 50% water
Coolant capacity (I)	456
Limiting ambient temp.** (°C)	50
Fan power (kWm)	33
Cooling system air flow (m³/s)**	34
Air cleaner type	Dry replaceable element with restriction indicator
** 0 10 110	•


^{** @ 13} mm H₂0


Fuel Consumption 1500 (50 Hz)

%	kWm	ВНР	L/hr	US Gal./hr				
Standby P	Standby Power							
100	1915	2567	437	115.3				
Prime Pow	Prime Power							
100	1730	2319	394	103.9				
75	1298	1739	291	76.9				
50	865	1160	200	52.7				
25	433	580	114	30.1				
Continuou	Continuous Power							
100	1415	1897	320	84.4				

Fuel Consumption 1800 (60 Hz)

%	kWm	ВНР	L/hr	US Gal./hr				
Standby Power								
100	=	=	-	=				
100	-	-	-	-				
75	-	-	-	-				
50	-	-	-	-				
25	=	=	-	=				
100	-	-	-	-				





^{*}Drawing for illustration purposes only.

Weights and Dimensions

Length	Width	Height	Weight (dry)	
mm	mm	mm	kg	
4979	2494	3201	9685	

Ratings definitions

Emergency Standby Power (ESP):	Limited-Time Running Power (LTP):	Prime Power (PRP):	Base Load (Continuous) Power (COP):
Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. Emergency Standby Power (ESP) is in accordance with ISO 8528. Fuel Stop power in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.	Applicable for supplying power to a constant electrical load for limited hours. Limited-Time Running Power (LTP) is in accordance with ISO 8528.	Applicable for supplying power to varying electrical load for unlimited hours. Prime Power (PRP) is in accordance with ISO 8528. Ten percent overload capability is available in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.	Applicable for supplying power continuously to a constant electrical load for unlimited hours. Continuous Power (COP) in accordance with ISO 8528, ISO 3046, AS 2789, DIN6271 and BS 5514.

For more information contact your local Cummins distributor or visit cummins.com

